

LOOP-THROUGH OUTLETS

LTO | Freja & Euro





PRODUCT OVERVIEW

| "521xx" | | Loop through | |
|---|------------------|-------------------------------------|--------------|
| Parameter | Frequency [MHz] | Freja LTO | Euro LTO |
| Item No. (Complete coax outlet) | - | 52140 | 52150 |
| Version | - | Terminated Transparent | |
| Screws, Claws and elastics band included | - | Yes | |
| Output | | | |
| Insertion loss [dB] | 5 - 204 | < 0.3 | |
| Innert 0 Output | 204 - 1218 | < 0.7 | 7 |
| Input & Output Return loss | 5 - 1218 | IEC 60729-4 | 85.7.4.2 |
| | 5 - 1210 | IEC 60728-4 §5.3.4.2 0.41 - 1.13 | |
| Cable center conductor diameter [mm] | | 0.41 - 1.15 | |
| | Center conductor | 7 mm | |
| | Dielectric | 2 mm | |
| | | | |
| | Braid | 9 mm | |
| | | | |
| | | | |
| Cable outer Jacket diameter [mm] | | 3.5 - | 8 |
| Common | | | |
| | 5 - 30 | | |
| Screening effectiveness [dB] | 30 - 300 | > 85 | |
| | 300 - 470 | > 80 | |
| | 470 - 1218 | > 75 | |
| Operating temperature [°C] | - | 0 - 55 | |
| Max dimensions (H x W x D) [mm] | - | 76,2 x 50 x 27.7 | 81 x 81 x 38 |
| Metal Housing | - | RoHS compliant Zink alloy | |
| Face plate material Included Face plates 1) | - | ABS | ABS |
| included race plates " | Туре | FFP-LTO | EFP-LTO |
| White | Item No. | 52142 | 52152 |
| | Туре | FFP-LTO-G | |
| Light grey face plate | Item No. | 52143 | |
| Antracite face plate | Type | FFP-LTO-KG | - |
| | Item No. | 52144 | |
| ncluded tamper detction sticker | | | |
| Indicator for unauthorized opening | Type | FTS | ETS |
| | Item No. | 52141 | 52151 |
| Included wall mounting box | | | |
| White wall box | Type | - | UBH |
| | Item No. | _ | 52808 |

¹⁾ Please see last page



ADDITIONAL INFORMATION

- Loop-through without external ports, fitted with tamper detection sticker.
- E.g. to bypass 1st floor and still provide signal to 2nd floor.

Freja LTO

White + Light Grey + Anthracite faceplates included **Item no. 52140**





Euro LTO
White faceplate included
Item no. 52150



